



3G MOBILE SETTING

CREATE THREE ACCESS POINTS FOR 3G SERVICE SURFING:


1. 3G WAP SETTING

1. Press **Menu**  ▶ Select **Tools** ▶ **Settings** ▶ **Connection** ▶ Select **Access Points**
2. Press **Options** ▶ Select **New Access Point:**
 - **Connection Name:** Camshin 3G WAP
 - **Data Bearer:** <Leave default>
 - **Access Point Name:** Camshin
 - **User Name:** <Leave default>
 - **Prompt Password:** <Leave default>
 - **Password:** <Leave default>
 - **Authentication:** <Leave default>
 - **Homepage:** <Leave default>
3. Press **Options** ▶ Select **Advanced Settings:**
 - **Network Type:** <Leave default>
 - **Phone IP Address:** <Leave default>
 - **DNS Address:** <Leave default>
 - **Proxy Server Address:** 172.16.203.85
 - **Proxy Port Number:** 8080

2. INTERNET WEB SURFING & 3G BASIC SERVICE



- A. Press **Menu**  ▶ Select **Tools** ▶ **Settings** ▶ **Connection** ▶ Select **Access Points**
- B. Press **Options** ▶ Select **New Access Points**
 - **Connection Name:** Camshin 3G
 - **Data Bearer:** <Leave default>
 - **Access Point Name:** Camshin
 - **User Name:** <Leave default>
 - **Prompt Password:** <Leave default>
 - **Password:** <Leave default>
 - **Authentication:** <Leave default>
 - **Homepage:** <Leave default>

3. MMS SETTING

1. Go to **Menu**  ▶ Select **Tools** ▶ **Settings** ▶ **Connection** ▶ **Access Points**
2. Press **Options** ▶ Select **New Access Point:**
 - **Connection Name:** Camshin MMS
 - **Data Bearer:** <Leave default>
 - **Access Point Name:** <Leave default>
 - **User Name:** <Leave default>
 - **Prompt Password:** <Leave default>
 - **Password:** <Leave default>
 - **Authentication:** <Leave default>
 - **Homepage:** http://172.16.205.10:38090
3. Press **Options** ▶ Select **Advanced Settings:**
 - **Network Type:** <Leave default>
 - **Phone IP Address:** <Leave default>
 - **DNS Address:** <Leave default>
 - **Proxy Server Address:** 172.16.203.85
 - **Proxy Port Number:** 8080

E-MAIL CONFIGURATION



1. Go to **Menu**  ▶ Select **Message**
2. Press **Options** ▶ **Settings** ▶ **E-mail** ▶ Open **Mailboxes**
(If you use this function first time, it will prompt: "No mailbox defined. Define now". Follow the guide to define a new mailbox)  **Options** ▶ **New mailbox**
3. Select mail type as **IMAP4** or **POP3** (select **POP3**)
 - **My e-mail address:** <Your email address>
 - **Incoming mail server:**
<Your incoming mail server name>
 - **Outgoing mail server:**
<Your ISP outgoing server name>
 - **Access point in use:** Select **Camshin 3G**
 - **Mailbox name:** <Your mail box name>(Ex: mymail)

3. Back to **Mailboxes** ▶ Select **mymail** ▶ Press **Options** ▶ Select **Connection Settings:**

1. Incoming E-mail:

User name: <Your e-mail ID>
Password: <Your e-mail password>
Incoming mail server: <Your incoming mail server name>(if defined, leave default)
Access point in use: Select **Camshin 3G** (if defined, leave default)
Mailbox name: <Your mailbox name>
Mailbox Type: **POP3**
Security (ports): <Leave default>
Port: <Leave default>

APOPsecure login: <Leave default>

2. Outgoing E-mail:

My e-mail address: <Your e-mail address>

(if defined, leave default)

User name: <Your e-mail ID>

Password: <Your e-mail Password>

Outgoing mail server: <Your ISP outgoing server name>(if defined, leave default)

Access point in use: Select **Camshin 3G** (if defined, leave default)


Security (ports): <Leave default>
Port: <Leave default>

▶ Select **User settings:**

- **My name:** Your name
- **Send message:** <Leave default>
- **Send copy to self:** <Leave default>
- **Include signature:** <Leave default>
- **New e-mail alerts:** <Leave default>


MMS CONFIG.



1. Press **Menu**  ▶ Select **Messages**
2. Press **Options** ▶ Select **Settings** ▶ Select **Multimedia messages**
 - **Image size:** <Leave default>
 - **MMS creation mode:** <Leave default>
 - **Access point in use:** **Camshin MMS**
 - **Multimedia retrieval:** <Leave default> or **Always automatic**
 - **Allow anon.msgs:** <Leave default>
 - **Receive adverts:** <Leave default>
 - **Deny report sending:** <Leave default>
 - **Message validity:** <Leave default>


VIDEO STREAM CONFIG.



1. Press **Menu**  ▶ Select **Application** ▶ Select **Realplayer** ▶ Press **Options** ▶ Select **Settings** ▶ Select and open **Streaming:**
 - **Proxy:** <Leave default> ▶ Select **Network:**
 - **Default Access Point:** Camshin 3G
 - **Online Time:** <Leave default>
 - **Lowest UDP Port:** <Leave default>
 - **Highest UDP Port:** <Leave default>
2. Press **Menu** ▶ Select **Web**
3. Press **Options** ▶ **Navigation Options** ▶ Select **Go to web address**
4. Input the Video Stream address you want to see (Such as http://172.16.206.16:8080/testportal.html).
 - Press **Go to** ▶ Select **Access point:** Camshin 3G

3G WAP/WEB BROWSING



1. Press **Menu**  ▶ Select **Web**
2. Press **Options** ▶ Select **Navigation options** ▶ Select **Go to web address**
3. Input the WAP address you want to browse (such as http://www.waplinks.com) ▶ Press **Go to** ▶ Select **Access point:** **Camshin 3G WAP**
4. Input the Web address you want to browse (such as http://www.yahoo.com) ▶ Press **Go to** ▶ Select **Access point:** **Camshin 3G**